



*The 2968 TETRA  
Radio Test Set for  
comprehensive mobile and  
base station testing*

- Automatic test programs for mobiles
- Call processing for all TIPv2 radios.
- Supporting Simplex and Duplex Operation, Group and Individual calls using either direct or hook signalling.
- On-channel TETRA transmitter measurements for manufacturing and installation
- T1 test signal generator supports conformance tests
- Comprehensive TETRA modulation analysis with constellation and phase trajectory analysis
- Uplink test signal for base receiver testing
- Base station control channel simulation to provide effective network simulation
- Error vector analysis

The 2968 is the world's leading TETRA radio test set, addressing the testing needs of TETRA terminals and base stations.

The 2968 TETRA radio test set performs the on-channel transmitter measurements required in TETRA production, installation, commissioning and service environments. Burst and continuous power measurements, vector modulation accuracy, timing error and frequency error are supported. Receiver measurements are supported by generation of the T1 test

signals. The 2968 is also capable of supporting the main world-wide trunking format (MPT 1327), GSM digital cellular and all of the international analog cellular standards (TACS, AMPS and NMT).

Based on the methods specified in the ETSI TETRA specifications, the 2968 has been designed to test all of the key RF, audio and DC parameters of a TETRA radio. Repeatable tests are carried out quickly and easily using built in auto test routines. Flexibility is retained, the built-in test routines can be used as supplied or tailored to suit specific requirements.

#### **TETRA Functionality**

The development of the 2968 has been phased to provide increasing TETRA functionality as the TETRA market moves from manufacture and installation through to maintenance and service.

The 2968 is capable of emulating the environments of the TETRA mobile, base station and direct mode terminal, providing a one instrument test solution for the TETRA air interface. To satisfy the wide range of future applications, the 2968 covers the frequency range of 10 MHz to 1 GHz.

Ongoing development will add further functions to the current 2968 by field upgrades.

#### **TETRA Measurements**

The 2968 provides the capability to make a range of essential measurements on an active TETRA transmitter.

Transmitter measurements on mobiles, base stations and direct mode TETRA terminals can be made via the intuitive user interface. Measurements include transmitter power, both burst and continuous, and burst profiles for all major

## 2968 TETRA Radio Test Set



burst types. Modulation accuracy, for both peak and RMS vector error, as well as burst timing error can also be measured. Constellation and phase trajectory displays provide a graphical indication of vector error. Decoded data is also available for display and is selectable by burst type.

The 2968's signal generator provides T1 test signals, defined in ETS 300 394-1, for performing receiver and transmitter tests on mobiles which implement a T1 test mode. The 2968 can generate a Main Control CHannel (MCCH) or Traffic CHannel (TCH) to support manufacturer-specific test modes.

For base station receiver testing, the 2968 synchronizes to the multiframe timing of the downlink signal generated by a TETRA Base Station, and transmits an uplink T1 type 7 (TCH/7.2) test signal to the base station receiver. Alternatively the 2968 can synchronise to an external TTL trigger pulse to allow synchronisation with the main transmitter switched off. These features provide the signal required to enable the base station to measure its own receiver Bit Error Rate, without the need of a separate signal generator or an external synchronization signal.

For mobile station testing the 2968 supports call processing performed by TETRA radios from all currently known manufacturers. The call processing functions include registration, de-registration, individual, group and telephone call set up, mobile-originated and mobile-terminated call set up, plus audio loopback (talk-back) and 1 kHz tone generation for simplex and duplex radios. Applications for call processing include production final test, screening prior to installation, and maintenance testing. The

general functionality of a radio can be tested quickly and easily before use on a live system.

The 2968 also includes:-

- Slot selection to enable transmitter measurements to be made on a particular time slot.
- Bit Error Rate (BER) meter for measuring mobile station receiver performance with a downlink T1 type 1 (TCH/7.2) signal, using T1 Loopback.
- Standard TETRA channel numbering plans for 380, 410, 450 and 870 MHz bands.
- Flexible duplex offset + channel spacing, using user definable systems.
- The T1 test signal enables transmitter frequency error to be measured and also exercises the TETRA link control to adjust transmitter power.
- Vector error versus time displays

Latest 2968 Phase 3 enhancements include:

- Built in Automatic test programs (Terminal).
- Cell re-selection and Call restoration supported (undeclared, unannounced, announced type 3 and 2) for true inter-cell handover testing.
- Open loop and Closed loop power control supported.
- Group attachment, detachment and selection supported. Selected and attached GSSI displayed.
- Mobile originated STATUS or SDS (Short Data Service) messages acknowledged and displayed.

### Operation

Single or dual port duplex test modes of operation are available, configurable for high power or high sensitivity measurements.

Dependent upon options purchased, the full range of TETRA features is available under local or remote operation. The high resolution display and 22 associated softkeys enable selection of all the major test modes. The Duplex screen displays both the stimulus to the radio receiver and the response from the transmitter, softkeys allowing selection of the display format for the results. Alternatively the display can be confined to one signal path only, either Rx or Tx.

In Rx test mode the receiver under test can be stimulated using a T1 test signal, control channel or traffic channel whose level and frequency can be varied. The Tx test mode provides measurements of all the major on-channel parameters. Selection of the measurement type such as burst power profile, spectrum analyzer or vector diagram produces the appropriate display whilst maintaining all the other measurement parameters on screen. The measurement displays can be expanded to occupy the full screen when more detailed analysis is required.

### REMOTE Operation

The 2968 provides remote control of all the major functions. Control can be exercised by either GPIB or RS-232.

### STANDARD FEATURES

The 2968 follows the IFR philosophy of offering a comprehensive package with all the essential features for testing in the radio environment, including:-

- Full span Spectrum Analyzer for signal tracking and alignment.
- Tracking Generator with variable level and offset tracking for gain and loss measurement, including mixer stages.
- Single port and two port Duplex test modes enabling measurement before or after the duplexer/combiner.
- FFT analyzer for audio analysis giving rapid display update with narrow resolution bandwidths.
- Variable frequency SINAD and distortion measurement for customized applications.
- Range of selectable Audio filters for versatile audio characterization.
- Comprehensive audio generators, with up to six sources enabling complex signaling to be generated without additional oscillators.
- Broad band and selective power meters to enable measurement of total transmitted power or power in a specific channel.
- Built-in multimeter, on the bench when you need it.

### Spectrum Analysis

The RF spectrum analyzer allows analysis of signals applied either directly to the RF ports or off-air via an antenna.

It carries many features usually found only on stand alone analyzers such as full span, selectable resolution bandwidth filters and two steerable markers.

In a TETRA environment the spectrum analyzer max hold facility allows TDMA signals to be displayed. For alignment of IQ mixers, carrier leakage and image rejection can be displayed. For RF module characterization and radio alignment a tracking generator facility is provided. Additionally the tracking generator can be programmed with a fixed frequency offset to characterize frequency converter stages, and  $\times 2$  or  $\div 2$  frequency ranges for doubler or divider stages.

### Optional Systems

The 2968 can be supplied with one or more options dependent upon user requirements. It can be configured with TETRA mobile (with or without Direct mode), TETRA base station or supplied with all three modes. This allows the customer to choose either to have the full TETRA system or leave it as a more specific tool to suit his current application yet allowing for upgrading at a later time. The 2968 may also be equipped with analog trunking, analog cellular and digital cellular systems. This allows the current analog systems users to be prepared for the introduction of digital systems. The following systems are

available:

- TETRA Mobile
- TETRA Base Station
- TETRA Direct Mode
- MPT 1327/MPT 1343 Trunked Radio
- PMR Test for AM/FM/FM radios.
- NMT Cellular Radio
- AMPS Cellular Radio (inc. N-AMPS)
- TACS Cellular radio (inc. N-TACS)
- GSM Digital Cellular (900 MHz)

For analog trunking and cellular testing IFR is established as the industry standard. The 2968 provides the fundamental measurements required (e.g. broadband power, FM deviation, SINAD) and a range of advanced facilities, such as the unique 40 kHz FFT analyzer.

### Concise easy to read printouts

The 2968 produces printouts at the touch of a key. This enables measurement results to be added to test reports and service notes.

Additionally, for analog systems and GSM, printouts can be stored on PCMCIA2 memory card.

### Size and Weight

Not only does the 2968 have the performance you would normally expect to see on a bench full of instruments, it also weighs under 19.5 kg (43 lb), so it is portable too.

## Specification

Certain characteristics are shown as typical. These provide additional information for use in applying the instrument but they are unwarranted.

TETRA Signal Generator	
<b>FREQUENCY</b>	
<b>Range</b>	10 MHz to 1 GHz, useable to 1.15 GHz
<b>Resolution</b>	1 Hz
<b>Indication</b>	4 digit display (channel number) in SYSTEMS mode 10 digit display (Hz) in Duplex mode
<b>Setting</b>	SYSTEMS mode: Channel number and frequency plan. Other modes: Keyboard entry (Hz), delta increment/decrement function and rotary variable control.
<b>Accuracy</b>	As frequency standard
<b>OUTPUT LEVEL</b>	
<b>Range</b>	One-port Dx modes: N-Type socket: -135 dBm to -50 dBm TNC socket: -135 dBm to -30 dBm Rx Test and two-port Dx modes: N-Type socket: -135 dBm to -40 dBm TNC socket: -135 dBm to -20 dBm
<b>Resolution</b>	0.1 dB
<b>Indication</b>	4 digits plus sign (dBm)
<b>Accuracy</b>	N-Type socket: $\pm 1$ dB (TETRA modulation) over the temperature range 15 to 35°C. Otherwise $\pm 1.2$ dB up to 575 MHz $\pm 1.75$ dB up to 1 GHz for levels above -120 dBm.

±1.3 dB up to 1 GHz over the temperature range 15 to 35°C.

#### Carrier On/Off

Keyboard operation, reduces signal generator output to less than -120 dBm

#### Reverse Power Protection

N-Type socket: With instrument switched on 150 W. Overload indicated by visual and audible warning. TNC socket: Protection up to 10 W. Reset available on removal of RF power. Excess power indicated by visual and audible warnings.

#### Output Impedance

50 Ω nominal

#### VSWR

N-Type socket: better than 1.2 up to 500 MHz; better than 1.3 up to 1 GHz (typically 1.2). TNC socket: typically 1.3 at 900 MHz.

#### RF Carrier Leakage

Less than 0.5 μV PD generated at the carrier frequency in a 50 Ω load by a 2 turn loop 25 mm or more from the case with output level set to below -60 dBm and terminated in a sealed 50 Ω load.

### TETRA Modulation

#### Frequency Range

10 MHz to 1 GHz, useable to 1.15 GHz

#### Modulation Rate

18 k symbols/sec

#### Modulation Filter

Root Nyquist,  $\alpha = 0.35$

#### Vector Error

<3% RMS  
<6% peak

#### Residual Carrier Power

<-35 dBc

#### Data

T1 test signals (in accordance with ETS 300 394-1)  
T1 type 1 (TCH/7.2 downlink)  
T1 type 2 (SCH/F downlink)  
T1 type 4 (TCH/2.4 downlink)  
T1 type 7 (TCH/7.2 uplink)

Control Channel (MCCH)  
Traffic Channel (TCH)

### TETRA Transmitter Measurements

#### Frequency Range

10 MHz to 1 GHz

#### Dynamic Range

0 dBm to +52 dBm

#### Burst Types Measured - Base Station Test

NDB - Normal Down Link (cont.) using TS1 or TS2  
SB - Synchronization Burst (cont.)  
NDB - Normal Down Link (discont.) using TS1 or TS2  
SB - Synchronization Burst (discont.)

#### Burst Types Measured - Direct Mode Mobile Test

DNB - Direct mode Normal Burst using TS1 or TS2  
DSB - Direct mode Synchronization Burst  
DSB - Direct mode Synchronization Burst (cont.)

#### Burst Types Measured - Mobile Test

CB - Control Burst (Half Slot discont.)  
NUB - Normal Uplink Burst (discont.) TS1 or TS2  
NUB - Normal Uplink Burst (cont.) TS1 or TS2

#### RF RELATIVE FREQUENCY ERROR METER

Mobiles test mode only

#### Frequency Error Range

±500 Hz

#### Burst Types Measured

CB, NUB (discont.), NUB (cont.)

#### Resolution

10 Hz

#### Indication

3 digits and bar chart with peak hold

#### Accuracy

±15 Hz

#### RF ABSOLUTE FREQUENCY ERROR METER

Base Station and Direct Mode test modes only

#### Frequency Range

10 MHz to 1 GHz

#### Dynamic Range

0 dBm to +52 dBm

#### Frequency Error Range

±500 Hz

#### Resolution

0.1 Hz

#### Indication

3 digits and bar chart with peak hold

#### Accuracy

±15 Hz + frequency standard accuracy

#### TETRA RF POWER METER

##### Power Measurement

Average power during one burst  
Measured at the symbol points  
Measured through TETRA filter  
(Root Nyquist  $\alpha = 0.35$ )  
Averaged over n bursts  
(selectable between  $n = 1$  to  $n = 250$ )

##### Indication Units

dBm

##### Resolution

0.1 dB

##### Indication

3 digits and bar chart with peak hold

##### Accuracy

±0.6 dB for temperatures in the range 15 to 35°C  
See also under Environmental - User Calibration.

#### BURST TIMING ERROR

##### Range

±510 symbols

##### Resolution

0.01 symbols

##### Indication

5 digits

##### Accuracy

±0.05 symbols

#### TETRA MODULATION ANALYZER

##### Modulation Error Range

20% RMS Vector error  
40% Peak Vector error  
20% Residual Carrier

##### Resolution

0.25%

##### Indication

4 digits and bar chart with peak hold  
Vector Error profile

##### Accuracy

±0.5% at 10% error

### Graphical Displays

#### RF POWER PROFILE

##### Vertical Scale

10 dB/div or 3 dB/div

##### Burst Type (Selectable)

BS, MS and DM-MS (Discontinuous only).

##### Power Measurement

Measured through TETRA filter  
Referenced (0 dB) to average power

##### Power Profile Dynamic Range:

50 dB

##### Indication

Power profile against TETRA template

##### Display

Complete Burst  
Ramp Up/Ramp Down

##### Time Spans

300 symbol periods for NUB, DNB, DSB, NDB, SB.  
150 symbol periods for CB  
Ramp Up/Ramp Down 2×25 symbol periods

##### Accuracy

±0.6 dB at symbol points for levels greater than -10 dB

#### CONSTELLATION DIAGRAM

Amplitude and phase at the symbol point  
Measured over all symbols of the burst  
( $SN_0 \sim SN_{max}$ )

Measured through TETRA filter

#### Display Features

Normal/Expanded

#### Display Mode

Single/Continuous  
Refresh/Persistence/Accumulate

#### PHASE TRAJECTORY DIAGRAM

Amplitude and phase continuously  
Measured over all symbols of the burst  
( $SN_0 \sim SN_{max}$ )  
Measured through TETRA filter

#### Display Features

Normal/Expanded

#### Display Mode

Single/Continuous  
Refresh/Accumulate

#### VECTOR ANALYSIS DISPLAYS

Vector, magnitude and phase displays  
Amplitude and Phase Continuous  
Measured over all symbols of the burst  
( $SN_0 \sim SN_{max}$ )  
Measured through TETRA filter

#### Display Features

Normal/Expanded

#### Display Mode

Single/Continuous

### RF Analog Signal Generator

#### Frequency Range

100 kHz to 1 GHz, useable 90 kHz to 1.15 GHz

#### Resolution

1 Hz

#### Indication

4 digit display (channel number) in SYSTEMS mode  
10 digit display (Hz) in Duplex mode

#### Setting

SYSTEMS mode: Channel number and frequency plan.  
Other modes: Keyboard entry (Hz), delta increment/decrement function and rotary variable control.

#### Accuracy

As frequency standard

#### OUTPUT LEVEL

##### Range

One-port Dx modes:  
N-Type socket: -135 dBm -40 dBm.  
TNC socket: -115 dBm -20 dBm.  
Rx Test and two-port Dx modes:  
N-Type socket: -135 dBm -10 dBm  
(-20 dBm with AM).  
TNC socket: -115 dBm +10 dBm  
(0 dBm with AM).

##### Resolution

0.1 dB

##### Indication

4 digits plus sign (dBm, dBμV, μV, μV PD/EMF)

##### Accuracy

N-Type socket:  
±1.2 dB up to 575 MHz  
±1.75 dB up to 1 GHz for levels above -120 dBm  
±1.3 dB up to 1 GHz over the temperature range 15 to 35°C

#### Carrier On/Off

Keyboard operation, reduces signal generator output to less than -120 dBm

#### Reverse Power Protection

N-Type socket: With instrument switched on 150 W. Overload indicated by visual and audible warning. TNC socket: Protection up to 10 W. Reset available on removal of RF power. Excess power indicated by visual and audible warnings.

#### Output Impedance

50 Ω nominal

#### VSWR

N-Type socket: better than 1.2 up to 500 MHz; better than 1.3 up to 1 GHz (typically 1.2). TNC socket: typically 1.3 at 900 MHz.

**SPECTRAL PURITY****Residual FM (CCITT weighted)**

Less than 6 Hz RMS up to 575 MHz.  
Less than 12 Hz RMS up to 1 GHz.

**Residual AM (CCITT weighted)**

Less than 0.05% RMS.

**Harmonics**

Better than -30 dBc for levels up to +7 dBm (TNC).  
Better than -30 dBc for levels up to -13 dBm (N-Type).

**Spurious signals**

Better than -45 dBc for carrier frequencies from 100 kHz to 36 MHz;  
Better than -50 dBc for carrier frequencies above 36 MHz.

**SSB Phase Noise (20 kHz offset)**

Better than -114 dBc/Hz up to 575 MHz  
Better than -108 dBc/Hz up to 1 GHz

**RF Carrier Leakage**

Less than 0.5  $\mu$ V PD generated at the carrier frequency in a 50  $\Omega$  load by a 2 turn loop 25 mm or more from the case with output level set to below -60 dBm and terminated in a sealed 50  $\Omega$  load.

**AMPLITUDE MODULATION – INTERNAL****Frequency Range**

100 kHz to 400 MHz, useable to 1.15 GHz

**AM Depth Range**

0 to 99%

**Resolution**

0.1%

**Indication**

3 digits

**Setting**

Keyboard entry, delta increment/decrement function and rotary variable control

**Accuracy <sup>(1)</sup> (up to 85% AM)**

$\pm 4\%$  of setting  $\pm 1$  digit for modulation frequency 1 kHz.  
 $\pm 6\%$  of setting  $\pm 1$  digit for modulation frequencies from 30 Hz to 10 kHz.  
 $\pm 8\%$  of setting  $\pm 1$  digit for modulation frequencies from 10 kHz to 20 kHz.

**Distortion**

Less than 1% at 1 kHz for modulation depths up to 30%, CCITT weighted.  
Less than 2% for modulation frequencies from 100 Hz to 20 kHz and depths up to 85%.

**Modulation Frequency**

Range: 20 Hz to 15 kHz for carrier frequencies up to 36 MHz; 20 Hz to 20 kHz for carrier frequencies up to 400 MHz.  
Resolution: 0.1 Hz below 10 kHz; 1 Hz below 20 kHz.

**AMPLITUDE MODULATION – EXTERNAL****Input impedance**

Nominally 1 M $\Omega$  in parallel with 100 pF

**Frequency Range**

As internal AM

**Modulation Frequency Range**

As internal AM with AC or DC coupling.

**Accuracy**

As internal  $\pm 2\%$

**Input Sensitivity**

1 VRMS for indicated modulation depth

**FREQUENCY MODULATION – INTERNAL****Frequency Range**

100 kHz to 1 GHz, useable 90 kHz to 1.15 GHz

**Indication**

4 digits

**Setting**

Keyboard entry, delta increment/decrement function and rotary variable control

**Accuracy <sup>(1)</sup>**

$\pm 3\% \pm 1$  digit at 1 kHz over the range 15 to 35 $^{\circ}$ C (0.1% per  $^{\circ}$ C outside this range).  
Typically  $\pm 3\% \pm 1$  digit for modulation frequencies from 20 Hz to 5 kHz.  
Typically  $\pm 7\% \pm 1$  digit for modulation frequencies from 5 kHz to 20 kHz.

Typically  $\pm 10\% \pm 1$  digit for modulation frequencies from 20 kHz to 75 kHz.

**Distortion <sup>(4)</sup>**

Less than 0.5% for modulation frequencies from 250 Hz to 5 kHz (for deviation 1 kHz to 800 kHz).  
Less than 1% for modulation frequencies from 50 Hz to 20 kHz (for deviation 1 kHz to 800 kHz).  
Modulation Frequency Range <sup>(6)</sup>  
20 Hz to 20 kHz Mod generators 1, 2, 3 or 20 Hz to 100 kHz Mod generator 4.

**Resolution**

0.1 Hz

**FREQUENCY MODULATION – EXTERNAL****Input Impedance**

Nominally 1 M $\Omega$  in parallel with 100 pF

**Frequency Range**

As internal FM

**Modulation Frequency Range**

DC to 100 kHz (DC coupled)  
10 Hz to 100 kHz (AC coupled)

**Input Sensitivity**

2.828 V pk-pk for indicated deviation

**Accuracy**

As internal  $\pm 2\%$  for frequencies up to 20 kHz

**PHASE MODULATION – INTERNAL****Frequency Range**

100 kHz to 1 GHz, useable to 1.15 GHz

**Indication**

4 digits

**Setting**

Keyboard entry, delta increment/decrement function and rotary variable control.

**Accuracy**

$\pm 5\% \pm 1$  digit for modulation frequencies from 250 Hz to 3.4 kHz, over the range 15 to 35 $^{\circ}$ C (0.1% per  $^{\circ}$ C outside this range).

**Distortion <sup>(4)</sup>**

Less than 1% for modulation frequencies from 250 Hz to 5 kHz (for deviation 1 rad to 160 rads).

**Modulation Frequency**

Range: 250 Hz to 5 kHz

**Resolution**

0.1 Hz

**PHASE MODULATION – EXTERNAL****Input Impedance**

Nominally 1 M $\Omega$  in parallel with 100 pF.

**Frequency Range**

As internal phase modulation

**Modulation Frequency Range**

250 Hz to 5 kHz

**Input Sensitivity**

2.828 V pk-pk for indicated deviation

**Accuracy**

As internal  $\pm 2\%$

**INTERNAL MODULATION AND AUDIO SOURCES**

Up to 6 tone sources can be assigned as 3 modulation generators and 3 audio tone generators.

**Modulation Modes**

Internal generators may be assigned to AM, FM,  $\Phi$ M.

**Audio Voltmeter****Input Impedance**

Nominally 1 M $\Omega$  in parallel with 100 pF.

**Frequency Range**

DC and 20 Hz to 500 kHz.  
AC only 20 Hz to 500 kHz.  
Polarized DC less than 10 Hz.

**Level Ranges**

0 to 10, 0 to 30, 0 to 100, 0 to 300 mV, 0 to 1, 0 to 3, 0 to 10, 0 to 30 V RMS reading (autoranging or fixed).

**Level Indication**

4 digits and bargraph with peak hold.

**Level Accuracy (DC Coupled) <sup>(3) (5)</sup>**

$\pm 2\%$  of reading  $\pm 1$  mV  $\pm$  resolution, DC and 100 Hz to 20 kHz.

$\pm 4\%$  of reading  $\pm 1$  mV  $\pm$  resolution, 40 Hz to 100 kHz.

**Level Accuracy (AC Coupled) <sup>(3)</sup>**

$\pm 2\%$  of reading  $\pm 1$  mV,  $\pm$  resolution 150 Hz to 20 kHz.  
 $\pm 4\%$  of reading  $\pm 1$  mV,  $\pm$  resolution 100 Hz to 100 kHz.

**Residual Noise**

100  $\mu$ V RMS CCITT weighted.

**Audio Frequency Meter****Range**

10 Hz to 500 kHz

**Resolution**

0.1 Hz from 10 Hz to 5 kHz  
1 Hz from 5 kHz to 50 kHz  
10 Hz from 50 kHz to 500 kHz

**Indication**

6 digits

**Accuracy**

As frequency standard  $\pm 1$  digit  $\pm$  resolution

**Sensitivity**

On bargraph greater than 25% FSD (DC coupled)

**Audio SINAD Meter****Frequency**

1 kHz default. User selectable up to 20 kHz

**SINAD Range**

5 to 50 dB

**Resolution**

0.1 dB for readings less than 20 dB  
0.2 dB for readings less than 25 dB

**Indication**

3 digits and bargraph with peak hold.

**Accuracy (bandpass filter selected)**

$\pm 0.5$  dB  $\pm$  resolution

**Sensitivity**

100 mV for 46 dB SINAD

**Audio Distortion Meter****Frequency**

1 kHz default. User selectable up to 20 kHz.

**Distortion Range**

0 to 100%

**Resolution**

0.1% distortion for readings greater than 1%.  
0.2% distortion for readings less than 1%.

**Indication**

3 digits and bar chart with peak hold.

**Accuracy**

$\pm 5\%$  of reading  $\pm$  resolution (bandpass filter selected).

**Sensitivity**

100 mV for 0.5% distortion

**Audio S/N Meter****S/N Range**

0 to 100 dB

**Resolution**

0.1 dB for readings less than 50 dB  
0.2 dB for readings less than 70 dB

**Indication**

3 digits and bar chart with peak hold

**Accuracy**

$\pm 0.5$  dB  $\pm$  resolution

**Sensitivity**

2 V for 60 dB, 200 mV for 40 dB

**Audio Oscilloscope****Operating Modes**

Single or Repetitive sweep

**Frequency Range**

DC to 500 kHz  
10 Hz to 500 kHz (AC coupled)

**Glitch Catching**

1  $\mu$ s minimum

**Voltage Ranges**

2 mV/div to 20 V/div in a 1, 2, 5 sequence

**Voltage Accuracy**

±5% of full scale

**Timebase**

5 µs/div to 10 s/div in a 1, 2, 5 sequence

**Timebase Accuracy**

As frequency standard

**Trigger Mode**

Auto trigger

**Marker Indication**

Level: M1-M2, M2-M1  
Time: M1-M2, M2-M1

**Graticule**

10 Horizontal by 8 Vertical divisions  
Can be magnified to full screen

**Audio FFT Analyzer****Span Widths**

50 Hz to 50 kHz in a 5, 10, 25 sequence.  
Above 40 kHz signals are attenuated by 80 dB/octave.

**Graticule**

10 Horizontal by 8 Vertical divisions  
Can be magnified to full screen

**Level Reference (top of screen)**

10 mV to 20 V, in a 1, 2, 5 sequence

**Level Accuracy**

±0.3 dB 100 Hz to 15 kHz; typically ±1 dB 40 Hz to 40 kHz

**Vertical Scaling**

1, 2, 5, 10 dB/div

**Dynamic Range**

60 dB

**Max hold facility****Audio Sweep facility**

DC to 20 kHz  
Marker Indication  
Level: M1, M2, M1-M2  
Frequency: M1, M2, M1-M2

**Audio Bar Charts**

Displays: AF voltage, SINAD, Distortion, S/N.  
Vertical Resolution: 1% of full scale.  
Ranging: Autoranging, range hold or manual selection (up/down), 1, 3, 10 sequence with hysteresis.  
With peak hold facility.

**Audio and Modulation Filters**

300 Hz Lowpass (±0.1 dB less than 150 Hz, ±0.2 dB, 150-200 Hz relative to 100 Hz).  
300 Hz to 3.4 kHz Bandpass (±0.4 dB, 400-2100 Hz relative to 1 kHz).  
5 kHz Lowpass (±0.3 dB at <3 kHz relative to 1 kHz).  
20 kHz Lowpass ±0.3 dB at <12 kHz, typically -0.9 dB at <15 kHz and -3 dB at 20 kHz relative to 1 kHz.  
CCITT Psophometric.  
C-MESSAGE.  
See also under Environmental - User Calibration.

**RF Frequency Meter****Range**

100 kHz to 1 GHz

**Resolution**

1 Hz or 10 Hz selectable

**Indication**

Up to 10 digits

**Accuracy**

As Frequency Standard ±2 Hz ± resolution

**Dynamic Range (Auto tuned)**

As RF Power Meter (broadband)

**Frequency Range (Auto tuned)**

10 MHz to 999.9 MHz

**Sensitivity**

Manual tuned: -100 dBm (TNC) dependent on receiver bandwidth in off air test mode

**Offset Frequency Range**

±1 MHz dependent on receiver bandwidth

**RF Power Meter (Broadband)****Frequency Range**

100 kHz to 1 GHz

**Dynamic Range (Auto tuned)**

10 mW to 150 W (N-Type), 100 mW to 0.5 W (TNC)

**Power Reading**

True mean power

**Indication Units**

Watts

**Resolution**

Better than 1%

**Indication**

3 digits and bargraph with peak hold

**Accuracy<sup>(5)</sup>**

100 kHz to 500 MHz:  
±7.5% (0.3 dB), 0.1 W to 50 W (N-Type).  
±10% (0.4 dB), 20 mW to 150 W (N-Type).  
±12% (0.5 dB), 200 mW to 50 mW (TNC).  
500 MHz to 1 GHz:  
±12% (0.5 dB), 20 mW to 150 W (N-Type).  
±15% (0.6 dB), 200 mW to 50 mW (TNC).  
100 kHz to 1 GHz:  
±7.5% (0.3 dB), 0.1 W to 50 W (N-Type) ±10% (0.4 dB)  
1 mW to 50 mW (TNC) for ambient temperatures in the range 15°C to 35°C.  
See also under Environmental - User Calibration.

**Maximum Safe Continuous Rating**

N-Type: 50 W.  
TNC: 0.5 W; overload protected to 10 W

**Intermittent Rating**

N-Type: 150 W for limited periods, typically 2 minutes at 20°C. Typical off to on ratio is 6:1.  
Overload indicated by audible and visual warning.

**RF Power Meter (Selective)****Frequency Range**

100 kHz to 1 GHz

**IF Bandwidth**

300 Hz to 30 kHz in a 1, 3, 10 sequence and 110 kHz, 280 kHz and 3 MHz

**Dynamic Range (Manually tuned)**

0 dBm to +50 dBm (110 kHz IF bandwidth) (N-Type)  
-90 dBm to +20 dBm (110 kHz IF bandwidth) (TNC)

**Power Reading**

Average

**Indication Units**

dBm

**Resolution**

0.1 dB

**Indication**

3 digits + bargraph with peak hold

**Accuracy<sup>(5)</sup>**

Typically ±2.5 dB N-Type & TNC.  
See also under Environmental - User Calibration.

**RF Spectrum Analyzer****Frequency Range:**

100 kHz to 1 GHz, useable from 30 kHz to 1.05 GHz.

**Spans**

500 Hz/div to 100 MHz/div, in a 1, 2, 5 sequence.

**Resolution Bandwidth**

300 Hz to 300 kHz in a 1, 3, 10 sequence and 3 MHz (automatically selected according to span and manually selectable).  
Video bandwidth - fixed at 3 kHz.

**Filter Shape**

Nominally 3 dB/60 dB, 1:11 (300 Hz to 30 kHz bandwidth)

**Reference Level (top of screen)**

-100 dBm to +70 dBm

**On Screen Dynamic Range**

80 dB

**Vertical Resolution**

0.5 dB on 10 dB/div, 0.05 dB on 1 dB/div

**Level Accuracy<sup>(5)</sup>**

Typically ±2.5 dB  
See also under Environmental-User Calibration

**Intermodulation Distortion**

Less than 80 dB for 2 signals on screen at reference level

**Phase Noise**

Typically -70 dBc / Hz at ±100 Hz from signal  
Typically -75 dBc / Hz at ±1 kHz from signal  
Typically -75 dBc / Hz at ±10 kHz from signal  
Typically -85 dBc / Hz at ±20 kHz from signal  
Typically -100 dBc / Hz at ±100 kHz from signal

**Sweep Speeds**

Optimum sweep speed selected according to span and resolution bandwidth

**Modes**

Single sweep and continuous

**Graticule**

10 horizontal by 8 vertical divisions

**Display Features**

Normal/Expanded

**Markers**

M1 and M2

**Indication**

Level: M1, M2, M1-M2  
Frequency: M1, M2, M1-M2

**TRACKING GENERATOR**

Available in RF TEST mode

**Frequency Range**

100 kHz to 1 GHz

**Level Range**

-135 dBm to +13 dBm

**Offset Tracking**

Allows testing of mixers, IFs, fundamental and 2nd harmonic analysis (up, down, x2, ÷2)

**Modulation Analyzer****Dynamic Range (Auto tuned)**

As RF Power Meter (Broadband)

**Sensitivity (Manual tuned)**

N-Type -30 dBm (110 kHz IF bandwidth)  
TNC -50 dBm (110 kHz IF bandwidth)  
TNC (off-air test mode) -101 dBm (2 µV 10 dB SINAD in 30 kHz IF bandwidth and CCITT weighting)

**Demodulation**

Accuracy maintained on signals greater than -60 dBm

**Receiver Bandwidths**

300 Hz to 30 kHz in a 1, 3, 10 sequence and 110 kHz, 280 kHz and 3 MHz

**Demodulation Filters**

As audio analyzer plus 5 kHz lowpass (±0.3 dB at less than 3.4 kHz relative to 1 kHz)

**Audio Output**

Available in to an internal loudspeaker, demodulated output or accessory socket for external loudspeaker or headphones  
Switching Speed  
Nominally less than 1 ms channel to channel up to 50 MHz apart, settling to within 1 kHz of final frequency

**Demodulated Output**

Nominal output impedance less than 10 Ω. Output voltage is range dependent (2 V peak at top of range).

**Squelch**

A manual squelch control is provided with a variable threshold

**AMPLITUDE MODULATION****Frequency Range**

100 kHz to 1 GHz

**Modulation Frequency Range**

20 Hz to 20 kHz

**AM Depth Range**

0 to 99.9%

**Resolution**

0.1% AM

**Indication**

3 digits and bar chart with peak hold

**Accuracy (up to 85% AM)** <sup>(4) (5)</sup>

±3% of reading, ±1% AM, 250 Hz to 5 kHz.  
Typically ±5% of reading, ±1% AM, 50 Hz to 15 kHz.

**Demodulation Distortion** <sup>(4)</sup>

Less than 1% at 1 kHz, CCITT weighted

**Residual AM**

Less than 0.1% AM, CCITT weighted

**FREQUENCY MODULATION****Frequency Range**

1 MHz to 1 GHz

**Modulation Frequency Range**

20 Hz to 20 kHz

**Deviation Range**

0 to 100 kHz

**Resolution**

10 Hz below 10 kHz deviation; 100 Hz below 100 kHz deviation

**Indication**

3 digits and bar chart with peak hold

**Accuracy** <sup>(4) (5)</sup>

±3% ± resolution for modulation frequency of 1 kHz  
±5% ± resolution for modulation frequencies from 100 Hz to 15 kHz

**Demodulation Distortion** <sup>(4)</sup>

Less than 0.5% at 1 kHz, CCITT weighted.

**Residual FM**

Less than 25 Hz RMS CCITT weighted

**PHASE MODULATION****Frequency Range**

1 MHz to 1 GHz

**Modulation Frequency Range**

250 Hz to 5 kHz

**Deviation Range**

0 to 20 rads

**Resolution**

0.01 rads

**Indication**

3 digits and bar chart with peak hold

**Accuracy** <sup>(4) (5)</sup>

±5% ± resolution

**Demodulation Distortion** <sup>(4)</sup>

Less than 0.5% at 1 kHz, CCITT weighted

**Audio Generators**

See section on modulation generators for interaction of audio and modulation generators.

**FREQUENCY****Range** <sup>(6)</sup>

1 Hz to 20 kHz AF Gens 1, 2 & 3 or 1 Hz to 100 kHz AF Gen 4.

**Setting**

Keyboard entry, delta increment/decrement function and rotary control.

**Indication**

6 digits

**Resolution**

0.1 Hz

**Accuracy**

As frequency standard

**LEVEL****Range**

0.1 mV to 5 V RMS (maximum AF output 7 V peak, all generators combined)

**Setting**

Keyboard entry, delta increment/decrement function and rotary control

**Indication**

4 digits

**Resolution**

0.1 mV

**Accuracy**

±3% ±1 digit, 250 Hz to 5 kHz  
±5% ±1 digit, 10 Hz to 20 kHz  
±10% ±1 digit, 20 kHz to 75 kHz

**Output Impedance**

Nominally 5 Ω

**Protection**

Maximum applied voltage 50 V

**SIGNAL PURITY****Distortion** <sup>(2)</sup>

Less than 0.5% at 1 kHz measured in a 30 kHz bandwidth.  
Less than 1% from 20 Hz to 20 kHz measured in an 80 kHz bandwidth.  
Typically 0.1% for levels greater than 100 mV

**Residual Noise**

Less than 50 mV RMS (CCITT weighted)

**DC Offset**

Less than 10 mV

**Signaling Encoder/Decoder****Sequential tones functions**

Encodes and decodes up to 40 tones.  
CCIR, ZVEI, DZVEI, EEA, EIA or user defined.  
Any of the tones may be extended.  
Continuous, burst and single step modes available.

**User defined tones**

Up to three frequency plans may be defined and stored within the 2968 for sequential tones.  
Any of the standard tone frequency plans may be copied to user defined and modified.  
Tone length 10 ms to 1 s.  
Extended tone length 100 ms to 10 s.

**CTCSS tones mode**

Standard tone frequencies may be selected from a menu

**DTMF Encoder/Decode**

Generation and decode of DTMF tones, displaying Hi/Lo frequencies, frequency error, timing information and twist.

**DCS Encode/Decode**

Generation and decoding of digitally coded squelch

**POCSAG generator**

Generation of POCSAG code CCIR No.1  
Rec 584. Bit rates from 400 to 9600 bit/s.

**Audio Monitor**

Audio and demodulation signals may be monitored via the internal loudspeaker or via the accessory socket output or BNC socket on the rear panel.

**SSB Option****SSB Tx**

Frequency, range and – as RF frequency  
meter accuracy – as Broadband power  
Power, level and meter accuracy  
Detection Range – 100 μV to 150 W  
AF Demod range – 10 Hz to 5 kHz  
Demod distortion – <2% @ 1 kHz CCITT weighted

Carrier and Alternate – Better than –50 dBc

s/band suppression

Sideband/CW Analyzer – -max 5 kHz full span frequency range

Spectrum Analyzer – -as RF spectrum analyzer

Audio Generator – -two – as audio generator

Sideband Selection – LSB, USB, CW

**SSB Rx**

Sideband Generator – as RF Gen (AM mode)

Offset measurement – to 0.1 Hz resolution

SINAD – as SINAD meter

Distortion – as Distortion meter

Note: No audio is available in SSB option

**General Features****INTERFACES**

Keyboard and Display  
Logical colour coded keyboard with bright high resolution CRT.

 **GPIB**

Full control of all major instrument functions via the

GPIB interface.

Flexibility is further enhanced by IFR's implementation of IEEE-488.2.

**Capability**

Complies with the following subsets as defined in IEEE-488.1-1978:- SH1, AH1, T5, TE0, L4, LEO, SR1, RL1, PPO, DC1, DT1, C1, E1.

**Serial**

Serial interface is provided for connection of RS-232 for instrument remote control. 9 Way socket. Control language is based on IEEE P1174.

**Parallel**

Connector 25 way female D-Type. Provides graphics screen dump. A selection of printer drivers are included.

**Accessory Socket**

Allows the connection of various optional accessories.

With suitable adapters is compatible with most 2955 series accessories.

**Memory Card**

Meets PCMCIA2/JEIDA – 4 standard. The memory card facility allows the storage of analog system test results and set ups.

**Video Output**

Color, compatible with most VGA monitors. 15 way Sub Miniature D Type.

**Frequency Standard****Internal Frequency Standard Output****Frequency**

10 MHz

**Level**

Nominally 2 V pk-pk

**Output Impedance**

Nominally 50 Ω

**Temperature Stability**

Better than 5 in 10<sup>8</sup>, 5 to 50°C

**Ageing Rate**

Better than 1 in 10<sup>7</sup> per year, after 1 month continuous use

**Warm Up Time**

Less than 10 minutes to within 2 in 10<sup>7</sup> at 20°C

**External Frequency Standard Input****Frequencies**

1, 2, 5 and 10 MHz

**Level**

Greater than 2 V pk-pk

**Input Impedance**

Nominally 1 MΩ in parallel with 40 pF

**Power Requirements****AC supply****Voltage**

88 V to 132 V and 188 V to 265 V

**Supply frequency**

45 Hz to 65 Hz

**Power**

Nominally 135 W, 260 W maximum, for future options

**Electromagnetic Compatibility**

Conforms with the protection requirements of Council directive 89/336/EEC.

Complies with the limits specified in the following standards:

EN55011 Class B	CISPR 11
EN50082-1	IEC 801-2, 3, 4
EN60555-2	IEC 555-2

**Safety**

Complies with IEC1010-1, BS EN61010-1 for class 1 portable equipment and is for use in a pollution degree 2 environment. The instrument is designed to operate from an installation category 1 or 2 supply.

**Environmental****Rated Range Of Use**

0 to 50°C and up to 95% relative humidity at 40°C

**User Calibration**

User calibrations are provided to maintain high accuracy for any ambient temperature (e.g. in ATE racks or in field measurements). Having allowed the instrument to stabilize, running the user calibrations optimizes the performance at that temperature. A change in temperature of 5°C from the calibration temperature affects readings as below. These figures are provided as a guide to typical performance. Typical variations are as follows for a 5°C change in temperature.

Power Meter:	Burst	0.5 dB
	Broadband	2%
	Selective	0.5 dB
Spectrum Analyzer Level		0.5 dB
Audio Analyzer & Modulation Filters		
	Audio Voltage	0.4%
	Demod depth & deviation	0.4%
Multimeter:	Voltage	0.5%
	Current	0.5%

**STORAGE AND TRANSPORT****Temperature**

-40 to +70°C

**Altitude**

Up to 2500 m (pressurized freight at 27 kPa differential).

**Internal Test Software****OPTION 10 NMT CELLULAR SOFTWARE**

<b>NMT450</b>	<b>NMT900</b>
Benelux	NMTF
Austria	Spain
Malaysia	Indonesia
Saudi 1	Saudi 2
Thailand	Oman
Tunisia	Hungary
Poland	Russia
Czech	Bulgaria
Slovenia	Turkey
USER DEFINED NMT	

**OPTION 11 AMPS CELLULAR SOFTWARE**

E-AMPS N-AMPS  
USER DEFINED AMPS

**OPTION 12 TACS CELLULAR SOFTWARE**

E-TACS TACS-2  
C-TACS I C-TACS II  
J-TACS N-TACS  
USER DEFINED TACS

**OPTION 13 MPT1327 TRUNKING SOFTWARE**

Band III JRC  
UK Water Hong Kong  
Autonet AMT  
Madeira NL-TRAXYS  
NZ MPT1327 PH-INDO  
USER DEFINED MPT

**OPTION 14 PMRTEST SOFTWARE**

USER DEFINED PMR for FM radios

**OPTION 21 GSM (900 MHz) DIGITAL CELLULAR SOFTWARE**

GSM Phase 1 and 2

**OPTION 30 TETRA MOBILE OPTION**

Systems: TETRA 380  
TETRA 410  
TETRA 450  
TETRA 870  
USER DEFINED TETRA

**OPTION 31 TETRA BASE STATION OPTION**

System: TETRA 380  
TETRA 410  
TETRA 450  
TETRA 870  
USER DEFINED TETRA

**OPTION 32 TETRA DIRECT MODE OPTION**

System: TETRA 380  
TETRA 410  
TETRA 450  
TETRA 870  
USER DEFINED TETRA

**General Features (Systems)****Test Modes**

Manual Test/Auto Test

**Manual Test Signaling Functions (TETRA)**

Registration (Location Update, all types)  
De-Registration  
Individual call  
Mobile Originated (MO) and Mobile Terminated (MT)  
Simplex and Duplex  
Hook Signaling and Direct Set-up  
Normal and Emergency  
Modification by Called Party (MT)  
Rejection by Called Party (MT)  
Transmit Request and Transmission ceased  
Cleardown from Mobile or from Test set

**Group Attachment**

Selected Group  
No Group  
Multiple Groups  
Command registration with Group Report

**Group Call**

Mobile originated (MO) and Mobile Terminated (MT)  
Normal and Emergency  
Transmit Request and Transmission ceased  
Cleardown from Mobile or from Test set

**Cell-Reselection <sup>(7)</sup>**

Undeclared  
Unannounced  
Announced Type 3  
Announced Type 2  
Call Restoration  
Neighbour Cell Broadcast

**Short Data Service**

Mobile Originated  
SDS Types 1,2,3  
Status (Acknowledged)

**Telephone Call**

Mobile Originated  
Normal and Emergency  
Cleardown from Mobile or from Test set

**Power Control**

Open Loop  
Closed Loop

**Auto Test Programs**

	<b>TETRA MS</b>	<b>GSM</b>	<b>Analog</b>
Call Processing Only	√	√	√
Call and RF Testing	-	√	√
Brief Testing	-	√	√
Comprehensive Testing	√	√	√
User Defined Test	√	√	√

**Digital Parametric Auto Test Routines**

	<b>TETRA MS</b>	<b>GSM</b>
Tx Timing	√	√
Tx Power Level	√	√
Tx Power Profile	√	√
Tx Frequency	√	√
Tx RMS Vector/Phase Error	√	√
Tx Peak Vector/Phase Error	√	√
Tx Residual carrier	√	-
Rx BER Class I	-	√
Rx BER Class II	-	√
Rx RBER Class Ib	-	√
Rx RBER Class II	-	√
Rx Frame Erasure	-	√
Rx Sensitivity	-	√
Rx RSSI Report	-	√

**Analog Parametric Auto Test Routines**

AF Frequency	AF Level
FM Deviation	Mod Frequency
Rx Distortion	Rx Expansion
Rx Sensitivity	Rx SINAD
Rx S/N	Tx Compression
Tx Distortion	Tx Frequency
Tx Level	Tx Power Level
Tx Limiting	Tx Mod Level
Tx Noise	Tx SINAD
Tx S/N	SAT Deviation
SAT Frequency	ST Duration
ST Frequency	ST Deviation
Data Deviation	DSAT Deviation

**Signaling Auto Test Routines**

Registration/Roaming Update  
Place Call  
Clear From Mobile  
Page/Call Mobile  
Handoff (Not TETRA)  
Clear From Land  
Speech Quality  
Hook Flash (Not GSM/TETRA)  
DTMF Decode (Not GSM/TETRA)  
Data Performance (Not GSM/TETRA)  
PTT On  
PTT Off  
Auto Test Pause Modes  
Pause Manual Only  
Pause On Failure  
Pause Always

**Dimensions and Weight**

Excluding handle, feet and covers.

<b>Height</b>	<b>Width</b>	<b>Depth</b>
177 mm (6.9 in)	370 mm (14.5 in)	540 mm (21.2 in)

Including handle, feet and covers.

<b>Height</b>	<b>Width</b>	<b>Depth</b>
203 mm (7.9 in)	420 mm (16.5 in)	600 mm (23.6 in)

**Weight**

Less than 19.5 kg (42.9 lb)

## Versions and Accessories

When ordering please quote the full ordering number information

- <sup>(6)</sup> Either 3 modulation plus 3 audio generators up to 20 kHz or 1 modulation or 1 audio generator to 100 kHz.  
<sup>(7)</sup> Cell re-selection functions require two test sets and a power splitter

### Ordering

#### Numbers

2968

#### Versions

TETRA Radio Test Set

#### Options

- Option 01 French Language Version
- Option 02 Spanish Language Version
- Option 03 German Language Version
- Option 08 Wideband FM
- Option 09 SSB Receiver Option
- Option 10 NMT Cellular Radio Option
- Option 11 AMPS Cellular Radio Option (including N-AMPS)
- Option 12 TACS Cellular Radio Option (including N-TACS)
- Option 13 MPT 1327/MPT 1343 Trunked Radio Option
- Option 14 PMRTEST for AM/FM/FM radios
- Option 21 GSM (900 MHz) Digital Cellular
- Option 22 Mobile Tuning Range Test
- Option 30 TETRA Mobile Option
- Option 31 TETRA Base Station Option
- Option 32 TETRA Direct Mode Option

Contact sales outlet for details of availability of options

#### Supplied with

- AC Supply Lead
- Operating Manual
- Programming Manual
- Multimeter Lead Kit (Two 4 mm leads to test points)

#### Accessories

- 54421/001 BNC Telescopic antenna.
- 54431/023 20 dB AF attenuator (BNC)
- 54112/158 Hard Transit Case
- 54112/157 Soft Carrying Case
- 54212/001 GSM Phase 2 Plug-In TEST SIM
- 54212/002 GSM Phase 2 Full Size TEST SIM
- 54127/310 Rack Mounting Kit
- 59000/189 Memory Card (128 K)
- 54411/052 600 Ω interface and 20 dB AF attenuator (Note 1)
- 46884/645 Accessory socket adapter (for use with 2955 accessories)
- 46884/646 Accessory Socket 'Y' adapter
- 46884/560 Parallel Printer Interface Cable.
- 46884/649 Serial port to PC Cable (25 way)
- 46884/650 Serial port to PC Cable (9 way)
- 43129/189 GPIB Cable
- 43130/596 Coaxial cable N-Type(m) to TNC(m) (double screened)
- 54311/095 Coaxial cable N-Type(m) to N-Type(m) (1 meter)
- 54311/071 TNC(m) to BNC(f) Adapter
- 54311/092 N-Type(m) to BNC(f) Adapter
- 52388/900 1 GHz Active Probe
- 54441/012 Power supply for probe 52388-900

**Note 1** – requires 46884-645 Accessory socket adapter

#### Applications

- 81514 TETRALOG MS Protocol Analyzer
- BaseTest - Customized PC based software for automated BS testing.

#### Service Support

The 2968 is supplied with a 2 year warranty as standard  
 W3 Third year warranty

Contact your local sales outlet for availability of these and other service plans.

#### NOTES

- <sup>(1)</sup> At low modulation levels the residual AM/FM may become significant.
- <sup>(2)</sup> At low audio levels the residual noise may become significant.
- <sup>(3)</sup> Audio and Modulation filter passband errors not included.
- <sup>(4)</sup> Typical performance figures are non-warranted.
- <sup>(5)</sup> Refer to USER CALIBRATION section.



IFR, 10200 West York Street, Wichita, Kansas  
 67215-8999, USA. E-mail: info@ifrsys.com  
 Tel: +1 316 522 4981 Toll Free USA: 1 800 835 2352 Fax: +1 316 522 1360

IFR, Longacres House, Norton Green Road, Stevenage, Herts  
 SG1 2BA, United Kingdom. E-mail: info@ifrsys.com  
 Tel: +44 (0) 1438 742200 Freephone UK: 0800 282 388 Fax: +44 (0) 1438 727601

As we are always seeking to improve our products, the information in this document gives only a general indication of the product capacity, performance and suitability, none of which shall form part of any contract. We reserve the right to make design changes without notice. All trademarks are acknowledged. Parent Company IFR Systems, Inc. © IFR. 2000.

