

_ _ _ _ _ d i g i t a l _ _ _ _ _	FCO	Level of Urgency +---+ F +---+	Page_1_ Of_3_
---	-----	---	------------------

FIELD CHANGE ORDER

Number: 62XMX-F001

Applicability:

This FCO applies to 6200 systems in European countries only. See problem below.

Problem/Symptom:

Replace cable assembly, 17-01567-01, on 6200 systems in European countries which must comply with VDE federal environmental regulations 523/1969 and 1046/1984.

Quick Check:

Check for two ferrite beads on the 17-01567-01 cable, Rev C1, which connects J5 at the XTC module to the console terminal's bulkhead at the rear of the system.

Compatibility/Prerequisite FCO: N/A

Est. Time to Install:

MTTI:.5 hr.

Special Tools or Test Equipment: N/A

FCO	Quantity:	Parts	Information
Order by		Part Number:	Description:
FCO Kit#:			
EQ-01543-01	1	17-01567-01	Rev "C1" cable assembly
FA-04849-01	1	FA-04849-01	FCO document

EQ Kit Variation System/Option Applic:

Approvals

CSSE Engineer Ken Jackson	F.S. Product Safety Robert Brister	F.S. Logistics Willie Ewing
CSSE Manager Jan Sicard	F.S. Microfiche Libraries VAX EP-FSVDC-LB	Affected Population: 275
MicroMedia Pub		Initial Kitting:

9. Scrap the old cable assembly.
10. Plug in the system. Apply power to the system by pushing the Circuit Breaker to the "ON" position. Power up the system by turning the upper key switch on the systems console panel clockwise to the "ENABLE" position.
11. Bring up the operating system.
12. Update the Site Management Guide to reflect this FCO.
13. Report the FCO activity on a LARS form in the "Module/fail area/FCO". (see attached example).

```

- - - - -
|d|i|g|i|t|a|l|
- - - - -

```

FCO 62XXM-F001

PAGE 3 OF 3

LARS EXAMPLE

CATEGORY F	USA	GIA	EUROPE
Activity -			
Contract and Warranty	W	U	Y
Non Contract/Non Warranty	F	F	F
RTD/Off-site Agreement	F		
DEC Option	62XXM	62XXM	62XXM
Type of Call	M	M	M
Action Taken	D	D	I
Fail Area-Module-FCO-Comments	62XXM-F001	62XXM-F001	62XXM-F001
Material Used	EQ-01543-01	EQ-01543-01	EQ-01543-01

(a) Warranty Optimum, Warranty Standard and Warranty Basic (on-site) Agreements.

(b) RTD=Return to Digital or Off-site Agreements; If Field Engineer On-site, use Activity Code "F".

```

\^ 62XXM
\\62XXM
\\JACKSON
\\1989
\\MAY
\\FCO_DOCS

```