

<pre>  _ _ _ _ _ _ _ _   d i g i t a l   _ _ _ _ _ _ _ _  </pre>	FCO	Level of Urgency +---+   I   +---+	Page__1 Of_11
--	-----	---	------------------

FIELD CHANGE ORDER Number: 85XBA-I007

Applicability: This FCO should be installed on all VAX 85X0 systems. It will change the revision of the VAX 85X0 systems to "F1".

| This revised FCO supersedes Rev. A released 27 July 1988. It has  
| been revised to correct steps 1 through 4 located on pages  
| 10 and 11.

Problem/Symptom: PC38N has a number of problems which can cause systems to crash and the Console to "Hang" or crash. A detailed problem list, along with the Console Release Notes is available over the ENET at VOLKS::NAUTILUS\$CONSOLE:RELEASE.32.

Quick Check: When the system is booted, it will automatically print the console microcode revision on the screen. It should be V8.0.

Compatibility/Prerequisite FCO: Implement on 8700/8800/8810/8820 Config. N and 897X per FCOs: 871BA-I003, 882BA-I005.	Est. Time to Install: 2.5 hrs.
---	-----------------------------------

Special Tools or Test Equipment:  
N/A

FCO	Quantity:	Part Number:	Description:
EQ-01523-01	1	FA-04823-01	VMB Patches Floppy
FA-04815-01	1		FCO Document

EQ Kit Variation System/Option Applic: N/A

#### Approvals

CSSE Engineer  
Jerry Harrigan

F.S. Product Safety  
Robert Brister

F.S. Logistics  
Ed Duggan

CSSE Manager  
Jan Sicard

F.S. Microfiche Libraries  
EP-FSNVX-LB VAX

Affected Population:  
4162

MicroMedia Pub.  
Ray LeBlanc

STARS

Initial Kitting:  
7043

Revision:

B

FCO Release Date

30-NOV-88

Hardcopy Publication:

2000

Parts Availability:

August 1988

```

- - - - -
|d|i|g|i|t|a|l|
|_|_|_|_|_|_|_|_|

```

FCO 85XBA-I007

PAGE 2 OF 11

```

*****
*           Instruction on getting Nautilus Console V8.0           *
*****

```

The complete Nautilus Console Application V8.0 is available at VOLKS::NAUTILUS\$CONSOLE or will be available in Diagnostic Release 32 July 15, 1988. You can copy the following nine (9) floppy images over the EasyNet.

VOLKS::NAUTILUS\$CONSOLE:

```

CSAX_CONSOLEDCL1.DSK;1 - Disk 1 - BL-FH39J-ME - COMMAND LANGUAGE
                                1/2 CONSOLE
CSAX_CONSOLEDCL2.DSK;2 - Disk 2 - BL-FH40D-ME - COMMAND LANGUAGE
                                2/2 CONSOLE
CSAX_NCON1.DSK;2        - Disk 3 - BL-FH41J-ME - RX100 CONSOLE TASKS
CSAX_NCON2.DSK;1        - Disk 4 - BL-FH42H-ME - RX101 ISP MICROCODE
CSAX_NCON3.DSK;2        - Disk 5 - BL-FH67J-ME - RX99 REVISION HISTORY
CSAX_NCON4.DSK;1        - Disk 6 - BL-FH43H-ME - RX102 BOOT COMMAND
                                FILES
CSAX_NCON5.DSK;1        - Disk 7 - BL-FI48F-ME - RX98 CI VMB SYSTEM
                                CODE
CSAX_NDIAG4.DSK;2       - Disk 8 - BL-FH05H-ME - RX107 MICRODIAG #1
CSAX_PATCHES.DSK;1     - Disk 9 - FA-04823-01 - Special VMS Patches

```

1. Copy the 9 files into your directory using COPY, FTSV, or other files transfer program.

```
$ COPY/LOG VOLKS::NAUTILUS$CONSOLE:CSAX_*.DSK *.*
```

2. Restore each of the 9 floppy backup files to individual floppies. (You need VOLPRO privilege to do the MOUNT command.)

```
$ MOUNT/FOR CSA1:
$ BACKUP/PHYSICAL filename.DSK/SAVE_SET CSA1:
$ DISMOUNT CSA1:
```

3. You now have a copy of Console Revision V8.0.



```
|_|_|_|_|_|_|_|_|_|
|d|i|g|i|t|a|l|
|_|_|_|_|_|_|_|_|_|
```

FCO 85XBA-I007

PAGE 4 OF 11

-----  
P/OS V3.2 DIRECTORY  
-----

NAUTILUS\$POS32 - Directory of all floppies needed to install P/OS V3.3

PROINSTALV32.DSK - BL-FJ70A-ME - P/OS INSTALLATION CONSOLE  
PROSYSTEMV32.DSK - BL-FH31C-ME - P/OS HARD DISK SYSTEM CONSOLE  
PROSETUPV32.DSK - BL-FH32C-ME - P/OS HARD DISK SETUP CONSOLE  
PROCTABV32.DSK - BL-FI92B-ME - P/OS SYSTEM SERVICES CONSOLE  
PROLIBRARV32.DSK - BL-FH33C-ME - P/OS LIBRARIES CONSOLE  
PRODRIVERS.DSK - BL-FI94B-ME - P/OS DRIVERS CONSOLE

SYNERGYV2.DSK - BL-FJ00A-ME - PRO/COMM SYNERGY CONSOLE 4/4  
PROCOMAV3.DSK - BL-FH36B-ME - PRO/COMM CONSOLE 1/4  
PROCOMBV3.DSK - BL-FH37B-ME - PRO/COMM CONSOLE 2/4  
PROCOMCV3.DSK - BL-FH38B-ME - PRO/COMM CONSOLE 3/4

PROBRU.DSK - BL-FJ72A-ME - P/OS BACKUP/RESTORE UTILITY

\*\*\*\*\*  
\* VAX 85X0/8700/8800/8810-N/8820-N/897X BASED CONSOLE \*  
\* INSTALLATION \*  
\*\*\*\*\*

If you install the Console Operating System, you need to install PRO/Communications and then install the CONSOLE/PRODCL application. If you need to install the CONSOLE/PRODCL application only, first remove the existing application by following the instructions below. To install the CONSOLE/PRODCL application, also follow the steps described below.

This installation procedure assumes that the Console already has P/OS V3.1 or V3.2 and PRO Communications V3.0 installed.

The CONSOLE/PRODCL application consists of eight diskettes, labeled as follows:

Order number	Volume Label	Title
BL-FH39J-ME	CONSOLEDC1	COMMAND LANGUAGE 1/2 CONSOLE
BL-FH40D-ME	CONSOLEDC2	COMMAND LANGUAGE 2/2 CONSOLE
BL-FH41J-ME	NCON1	RX100 CONSOLE TASKS
BL-FH42H-ME	NCON2	RX101 ISP MICROCODE
BL-FH67J-ME	NCON3	RX99 REVISION HISTORY
BL-FH43H-ME	NCON4	RX102 BOOT COMMAND FILES



SCREEN> key. The System Environment Services Menu will appear.

- g. At this menu select "Delete application from public library". The Delete Application From Public Library menu will appear.

```

-----
|d|i|g|i|t|a|l|
|_|_|_|_|_|_|_|
-----
FCO      85XBA-I007
PAGE     6   OF   11
```

- h. At this menu select "Application specific components". The Delete Application Specific Component Menu will appear.
  - i. From this menu select CONSOLE/PRODCL. An "operation in progress ..." message will appear at the bottom left of your screen. A \*\*NOTICE\*\* message may appear regarding system wide components. Press the <RESUME> key to continue.
  - j. The System Environment Services Menu appears. Select "Delete application from public library".
  - k. At the Delete Application From Public Library menu, this time select "System wide components".
  - l. The Delete System Wide Component Menu will appear. From this menu select "CONSOLE/PRODCL". Again an "operation in progress ..." message will appear.
  - m. The System Environment Services Menu will reappear when the deletion operation from the system library has completed. Proceed to step 3 C below.
3. With P/OS and PRO/Communications installed, install the CONSOLE/PRODCL application. The installation procedure is not drive specific, therefore, you may insert the application diskettes into either diskette drive.
    - a. From the main menu select Environment Services.
    - b. The User Environment Services menu appears. Press the <NEXT SCREEN> key to obtain the System Environment Services menu.
    - c. Insert the application diskette, volume label: CONSOLEDC11 into either diskette drive slot.

- d. From the System Environment Services menu select "Copy Application into Public Library".
- e. The Copy Application into Public Library Menu appears. Select "Entire Application".
- f. The Application Selection menu appears. Select "CONSOLE/PRODCL". Copying of the application into the public library will begin.

```

- - - - -
| | | | | | | |
|d|i|g|i|t|a|l|
|_|_|_|_|_|_|_|

```

FCO 85XBA-I007

PAGE 7 OF 11

- g. When the CONSOLEDC11 diskette is copied you are asked to insert the diskette labeled CONSOLEDC12. You should then remove the diskette labeled CONSOLEDC11, insert the diskette labeled CONSOLEDC12 into the diskette drive and press the <RESUME> key to continue.
- h. You are then asked to insert diskette NCON1. Remove the diskette labeled CONSOLEDC12. Insert the diskette labeled NCON1. Press the <RESUME> key to continue.
- i. You are then asked to insert diskette NCON2. Remove the diskette labeled NCON1. Insert the diskette labeled NCON2. Press the <RESUME> key to continue.
- j. You are then asked to insert diskette NCON3. Remove the diskette labeled NCON2. Insert the diskette labeled NCON3. Press the <RESUME> key to continue.
- k. You are then asked to insert diskette NCON4. Remove the diskette labeled NCON3. Insert the diskette labeled NCON4. Press the <RESUME> key to continue.
- l. You are then asked to insert diskette NCON5. Remove the diskette labeled NCON4. Insert the diskette labeled NCON5. Press the <RESUME> key to continue.
- m. You are then asked to insert diskette NDIAG4. Remove the diskette labeled NCON5. Insert the diskette labeled NDIAG4.

Press the <RESUME> key to continue.

- n. The System Environment Services menu will appear when the CONSOLE/PRODCL application has been copied to the Public Library. Remove all the diskettes and save them as backups. The next step is to install the CONSOLE/PRODCL application to the system account from the library.
4. We will now install the CONSOLE/PRODCL application just copied to the public library. In addition, we'll instruct the PRO that this is the application to be run each time the PRO is powered-on.

```
  _ _ _ _ _  
 | d | i | g | i | t | a | l |  
 | _ | _ | _ | _ | _ | _ | _ |
```

```
FCO      85XBA-I007  
PAGE     8   OF   11
```

- 
- a. Press the <PREV SCREEN> key. The User Environment Services menu will appear.
  - b. At this menu select "Install Application". The Application Source Menu will appear.
  - c. From this menu select "Library". The Application Library Menu will appear.
  - d. From the Application Library menu select "CONSOLE/PRODCL".
  - e. The Application Group Menu appears. From this menu select "Main Menu Applications".
  - f. The Application Group or Name Change Form menu will appear. Press the <DO> key . Copying of files will begin from the library to the system account.
  - g. The User Environment Services Menu will appear when copying is complete.
5. Now set the CONSOLE/PRODCL to be the first application.
- a. At the User Environment Services Menu select "First application". The Application Group Menu will appear.
  - b. From this menu select "Main Menu Applications". The Application Select Menu will appear.
  - c. From the Application Select Menu select "CONSOLE/PRODCL".



- d. The User Environment Services Menu will appear. Exit to Main Menu by pressing the <EXIT> key. Power the PRO OFF then ON to run the CONSOLE/PRODCL application. Before powering up, be sure \*ALL\* diskettes have been removed from the diskette drives.

The CONSOLE/PRODCL procedure is not complete until step 5d has been completed by switching the Console system unit to OFF (0) and then back ON (1).

NOTE: At this point you may see a new LOGFILE being created. Please wait until this operation has completed and the Console prompt, " >>>" , is displayed.

\*\*Remember to edit the new bootstrap command files.

```

|_|_|_|_|_|_|_|_|
|d|i|g|i|t|a|l|
|_|_|_|_|_|_|_|_|

```

```
FCO      85XBA-I007
```

```
PAGE    9  OF  11
```

```

*****
*                               INSTALLATION OF VMS PATCHES                               *
*****

```

1. Insert floppy CSAX\_PATCHES (FA-04823-01) into one of the PC38N's Floppy drives.

(CSA1 - Top/Left, CSA2 - Bottom/Right)

2. Log into VMS with the following privileges:

```

BYPASS
or
SYSPRV

```

3. Mount the floppy with the following DCL command:

```
$ MOUNT CSAx: PATCHS ! x = Which floppy drive you inserted the floppy disk.
```

4. Set your default directory to SYS\$SYSROOT:[SYSEXE] (Non Clustered system) or SYS\$COMMON:[SYSEXE] (Clustered systems).

```
$ SET DEFAULT SYS$xx:[SYSEXE] ! xx = COMMON or SYSROOT
```

5. Copy the following files from the floppy disk into the default directory:





VMB.EXE.

6. Update the Site Management Guide to reflect this FCO.
7. Report this FCO activity on the LARS form in the "Fail Area/  
Module/FCO/Comments" column as follows: FCO 85XBA-I007.

-----

LARS

	USA	GIA	EUROPE
Activity -			
Contract and Warranty	W	U	Y
Non Contract/Non Warranty	F	F	F
DEC Option	VAX 85X0	VAX 85X0	VAX 85X0
Type of Call	M	M	M
Action Taken	D	D	I
Fail Area-Module-FCO-Comments	85XBA-I007	85XBA-I007	85XBA-I007
Material Used	EQ-01523-01	EQ-01523-01	EQ-01523-01

\^ 85XBA  
\85XBA  
\85XBA-I007  
\HARRIGAN  
\1988  
\NOV  
\FCO\_DOCS