

## This Document apply to LY4x

### From version 1.1.x.x to newer version

#### Update the firmware

1. Reboot the switch , when see the following screen, please select item 3.  
Please choose which to start.(Will choose active entry if no input in 10 seconds)

Current boot mode: normal

=====Main Menu=====

- \*1 - Start Application (active)
- 2 - Start Diagnostic Application
- 3 - Utility

=====

Enter your choice (1-3): **3**

=====Utility Menu=====

- 1 - Format FLASH device to JFFS2 file system
- 2 - List file
- 3 - Delete file
- 4 - Download file
- 5 - Active file
- 6 - Reboot
- 7 - System Shell
- 8 - Exit

=====

2. Select 3 to delete the current run time file (select "2" first to check the run time image)
3. Select 4 to download the image  
Enter your choice (1-8): **4**  
Creating tmpfs filesystem on tmpfs for download...done.  
Enter TFTP Server IP : **192.168.2.100** <- Your tftp server  
Enter Host IP : **192.168.2.1**  
Enter Host Subnet Mask :  
Enter Gateway IP :  
Enter Filename : **image1** <- please rename your image name to image1  
Do you want to continue? Press(Y/N): **y**
4. Once finish the download then select 5 to select the image1 as the next boot.

Enter Filename : **image1**

Active application file image1...

5. Reload the switch.