



For OSF/1 environments with ASE/DECsafe software DWZZA's require the following minimum revisions:

Minimum revision (option level) DWZZA-AA rev. E01

Minimum revision (option level) DWZZA-VA rev. F01

Removing the DWZZA-AA option;

- 
- Step 1. Remove all SCSI bus traffic, from all the SCSI bus segments, attached to the DWZZA-AA.
  - Step 2. Remove unit power from DWZZA-AA with the toggle switch.
  - Step 3. Disconnect the power cord from the power source outlet.
  - Step 4. Disconnect the power cord from the DWZZA-AA receptacle.
  - Step 5. Remove all the SCSI cables attached to the DWZZA-AA.

Replace with DWZZA-AA option rev. E01 or greater.

- 
- Step 1. Re-attach all the SCSI cables to the DWZZA-AA.
  - Step 2. Connect the power cord to the DWZZA-AA power receptacle.
  - Step 3. Connect the power cord to the power source outlet.
  - Step 4. Turn on power to the DWZZA-AA with the toggle switch.

Removing the DWZZA-VA option;

- 
- Step 1. Remove all SCSI bus traffic, from all the SCSI bus segments, attached to the DWZZA-VA.
  - Step 2. Remove the SCSI cable attached to the DWZZA-VA.
  - Step 3. Remove the DWZZA-VA SBB from the BA350-XX.

Replace with DWZZA-VA option rev. F01 or greater.

- 
- Step 1. Plug the DWZZA-VA SBB back into the BA350-XX
  - Step 2. Re-attach the SCSI cable to the DWZZA-VA.

---

FIELD APPLICATION DOCUMENT (FA), Continuation Page

d	i	g	i	t	a	l
---	---	---	---	---	---	---

FCO DWZZA-AA-F002  
FCO DWZZA-AA-F001  
PAGE 3 OF 3

CATEGORY	F	USA	APA	EUROPE
Activity - Coverage Code				
(a)Contract		W	U	K
Warranty		W	U	W
Inhouse				A
Invoiced per Call				F
(b)IN-DEC Contract		K	U	
Non Contract/Non Warranty		F	F	
(c)RTD/Off-site Agreement		F	U	
Hardware Segment Code		111	111	
Product Line		031	031	
BBC Code for K,W,A				111
BBC Code for F				031

DEC Option		DWZZA-AA	DWZZA-AA	DWZZA-AA
or		DWZZA-VA	DWZZA-VA	DWZZA-VA
Option ID		X	N/A	N/A
Type of Call		M	M	
Request Type				I
Action Taken		D	D	Y
Quality Codes				M,L,J,R,X,A,Y,Z
Fail Area-Module	FCO	DWZZA-AA-F002	DWZZA-AA-F002	DWZZA-AA-F002
or	FCO	DWZZA-VA-F001	DWZZA-VA-F001	DWZZA-VA-F001
FCO-Comments				

Material Used				
DWZZA-AA		EQ-01705-01	EQ-01705-01	EQ-01705-01
DWZZA-VA		EQ-01710-01	EQ-01710-01	EQ-01710-01

- (a) Warranty Optimum, Warranty Standard and Warranty Basic (on-site) Agreements; \* Note material (only) free of charge for all customers.
- (b) Applies to IN-DEC Area Only
- (c) RTD=Return to Digital or Off-site Agreements; If Field Engineer On-site, use Activity Code "F".

FCO CHARGING INFORMATION								
WARRANTY/CONTRACT				NONWARRANTY/NONCONTRACT				
ON-SITE		OFF-SITE		ON-SITE		OFF-SITE		MATERIAL ONLY
TRAVEL/	EQ		EQ	TRAVEL/	EQ		EQ	ORDER-ADMIN,HANDLING
INSTALL	KIT	INSTALL	KIT	INSTALL	KIT	INSTALL	KIT	PKG,SHIPPING & EQ KIT
DEC	DEC	DEC	DEC	CUS	CUS	CUS	CUS	CUS